

GPS Watch Simple Manual



Preface

Thank you for purchasing the GPS Watch Tracker. This manual will show how to operate the device smoothly and correctly. Make sure you read this user manual carefully before using this product. Please note that specification and information are subject to changes without prior notice in this user manual. Any change will be integrated in the latest release of this product. The manufacturer assumes no responsibility for any errors or omissions in this document.

Summary

Working Based on existing GSM/GPRS network and GPS satellites, this product can locate and monitor any remote targets by SMS or GPRS.

Application

- Designed to safe guard children, the elderly, the disabled and can be used on pets
- Provides peace-of-mind for, for hikers, campers and outdoor extreme sports, such as boating, mountain climbing.
- Can be use to tracking criminals, and individuals under house arrest or surveillance

Function & Features

- Display shows the current time, date, longitude, Latitude, speed, direction, signal strength, power level etc.
- SMS & GPRS real-time tracking, support management platform
- It can store three phone numbers and can press any one of the call button to get help, or if you just need to talk.
- Two-way communication, hands free mobile phone function
- A SOS button for emergency help.
- Alarm with phone call and SMS
- SMS come with positioning link.
- Listen-in automatically when you call the tracker.
- Low power indication.

Appearance and Interface

1. Appearance and Buttons

Five buttons are equipped with this watch, **A** is the ON/OFF button, Press and hold for three seconds on or off; **D** is the menu and interface conversion function button, press one second conversion watch interface, Press and hold for three seconds to enter the main menu, After enter the menu, the **E** \ **F** buttons up and down selection menu, **G** button to confirm, **D** button to return; **E** button, In standby mode, press and hold three seconds dial the first phone number; **F** is SOS button, Press and hold for three seconds alarm; **G** In standby mode, press and hold three seconds dial the second phone number, as shown in picture 1:



2. Interface Definition

GSM signal strength is indicated on the upper left corner of the main interface as showed in picture 2:



Bottom left button is for interface switch as showed in picture 3:



Operation

(1) Switch ON/OFF the device

Long-press ON/OFF button for 3 seconds, then open the device and enter the main interface, long-press it again with 3 seconds ,then it will be closed.

(2) Mode switching

Press **Mode button** you can change the interface mode.

(3) SOS

Press SOS button ,it will call the pre-set number 1 , if there is an answer ,it will not call other pre-set number, if there is no answer from number 1 it will call number 2 and number in turn .



(4) Call pre-set number

You can call the pre-set number

When you press button "Call 1", the device will call the pre-set number 2.

When you press button "Call 2", the device will call the pre-ser number 3.

Then you can communicate with the other person with two-way mode.

(5) Answer the calling-in automatically.



If someone call the device then you will see the interface, you can answer it by pressing SOS button, otherwise it will answer automatically after 30 seconds, or you can hang up it by pressing ON/OFF button.

Operate it by SMS (default mode)

(1). Open the cover at the back of that watch, insert your SIM card, the insert the battery and close the cover.

(2). Walk **outdoors or near a window side** and press 3 seconds **switch ON/Off** button get into main page that time, longitude and latitude data, speed, direction are all shown up as 0, Once the device receives the satellite signal, it will check the time automatically (the English version rectify time is for **GMT Greenwich Mean Time**), using command "8960000 E08" can modify into Chinese time, please make reference following point (3).

(3) Setting time zone function

Command: 896xxxxDnn

Example: 8960000E08

The xxxx is four digits passwords, the D choose **E**astern or **W**estern that means time zone; The nn is two numerals (0~12) for time difference If setting success, the device will reply you with SMS confirming message:

Time zone: Eastern/ Western xx:

If the device is without any pre-set phone number, any number can send a command: 6660000
Where (0000 is password)

For example, the following message will be received when sending 6660000:

Lat: +22.56303

Long: +114.09362

Speed: 8.98KM/H

Direction: 62.58

Date: 2009-11-18

Time: 09:39:45 (Greenwich Mean Time, GMT)

BS: 27970eb3

FIX::A
ID: 356856789000001
STATE: SMS

If password is correct with sending 8960000E08 instructions, the time item should automatically add 8 modifications as Time:17:39:45 The same way that sending 8960000 W07 instructions, the Time item should automatically reduce 7 modification is Time: 02:39:45

(4) Single Locate by timing

(1) Making a phone call: Before settle authorization number, any number can call the swatch that ring 1-4 hang up after, can reply a message that all related information longitude and latitude, the position data can be searched on GOOGLE maps using your computer, calling in and ringing 5 times will prompt the device to automatically answer.

(2), message (SMS) Mode: before having settle authorization number, Any number can send out a message 6660000(0000 is Password) to the watch, replying the message of longitude and latitude position data, the message is same as which from making a phone call; Send out a message9870000 to the number, Reply to a URL, enter the URL will see the GPS location and address description ;Send out a message9880000 to the number, the address details will be received (only limit Chinese version)

(5)Pre-set /changing authorization number

(Note: Once the authorization number is set, it cannot be deleted, only changed)

Command: *mobile phone number*user's password*(1-3) **

For example:*13800000000*0000*1**

If 13800000000 is the number being pre-set, 0000 is a password, 1 is for the first number pre-set, You can preset three numbers at the most, only authorized numbers that call or send out a message, can receive a reply from the device detailing the longitude and latitude data, except it, other non presetted number wont be able to receive any information at all.

(6)Timing / position

Command: 4010000

Explain: The XX mean timing position partition for time, 01 means locate by one minute, if cancel timing you can send message: 4000000

(1) Search the machine ID code (non- machine the number of the back)

Making a phone call or sending command: 6660000, replying you that 15 digit ID code. For example ID: 356856789000001

Appendix:

- (1) #901## Command of inquiring machine parameters
- (2) #902## Command of inquiring GPRS parameters
- (3) #904## GPRS connection command
- (4) #905## GPRS disconnection command

• Package Contents

GPS Watch
Charger
USB Cable
Battery x2
Earphone(Optional)