(11)

Bluetooth & 2.4G Wireless Game Pad

Instruction Manual

Button Description



ANDROID BLUETOOTH GAME CONTROLLER USER MANUAL

Dear Customers.

Thank you for purchasing our product. This is a multi-function android game controller via bluetooth connection. For proper operation with optimum performance, please read this user manual carefully before connecting, operating or user his product. Please be noted that all information in this manual is based on factory default setting. All images and descriptions are for reference only. For practical conditions, please refer real product as standard. If there is any update for this user manual, it will be re-incorporated into the new version and without notice. Our Company reserves the right of final decision on the interpretation of this user manual. All available features and additional services may vary by device, software, or service provider. Please kindly understand if there are any typographical error translation errors. Thank you

1. Product Information

a) Mode Switching

Paired with Bluetooth Gamepad Mode : "A" Indicator Light ON
Remote Control Mode : "M" Indicator Light ON

Keyboard Mode : "K" Indicator Light ON iOS Mode : "I" Indicator Light ON

b) Application Platform

a) ANDROID System(verison 4.2 or above). Download platform is available to use.

b) iOS System(version iOS6.0 to 9.2). For iCade Mode, please switch your device to English input method before pairing.

c) Support PC/PC360/PS3 (PC/PC360 support Window XP or above version) via USB port connection

2. This game controller can be switched into different mode of use

1. ANDROID Gamepad Mode:

Press and hold "X" + "N1" button for 5 seconds to pair with code. 4 indicator lights will flash at the same time, Search and click "Game Pad". Once paired, Indicator light "A" turns on.

Press and hold "Y" + "N1" button for 5 seconds to pair with code. 4 indicator lights will flash at the same time, Search and click "Newgamepad N1". Once paired, Indicator light "K" turns on (This mode can only apply on APPLE IOS device, please download game platform before use.)

Press and hold "B" + "N1" button for 5 seconds to pair with code. 4 indicator lights will flash at the same time, Search and click "Game Pad". Once paired, Indicator light "I" turns on.

4. Remote Control Mode:

. Remote volutor move.
Press "N1" button to switch as remote control(mouse + multimedia) while using above 3 modes. Other buttons correspond to the following function: "A" Button(volume -), "B" Button(Velor Track), "X" Button(Previous Track), "L1" Button(Mouse Left Click), "L2" Button(Hgy), "R1" Button(Mouse Right Click/Back), "R2" Button(Hgy), "R1" Button(Mode), Left "Joystick" (Mouse with large range movement), Right "Joystick" (Mouse with fine movement), (Remarks: For IOS Mode, please switch your device to English input method first and this case does not support mouse function.)

3. Electrical Parameters

a.Operating Voltage: DC3.7V b.Operating Current : ≤40MA c.Quiescent Current : ≤80uA d.Internal Battery: 3.7V 400MA e.Charging voltage: DC5.0V f.Charging Current: 500MA-1000MA

4. Operating Instructions

1. LED Indicator: 4 Indicator lights "A", "M" "K", "I" can be represented as charging, low battery, mode and bluetooth pairing.

a) Hold "Select" button and press "N1" button then release to switch on USB pairing instantly.

b) Once connect to PC via USB port, Indicator light" A" turns on. It support PC Mode game controller function.
c) PC 380 game controller switching via the PC mode, hold "Select" + "Start" button for 4 seconds, Indicator light "K" turns on.
d) When connect with PS3 via this port, indeed to elentified as a "P3" to PS3 machine automatically and 4 indicator lights will be changed as gateway function.

3) Auto Connect :

a) Android/iOS device (Bluetooth ON). The game controller (OFF). Press "N1" button to turn it on, it will connect with your device again. b) Android/iOS device(Bluetooth OFF). The game controller(ON), Turn on the bluetooth function on your device, it will connect your game

c) Android/IOS device(Bluetooth OFF). The game controller(OFF). Turn on the bluetooth function on your device. Press game controller "N1" button to turn it on, they will connect again.

Remarks: To fulfill above status, the game controller and the device must successfully paired before and with pairing record must be retained. Usually, the connection will appear in few seconds automatically. If the pairing record has been removed, the indicator light will flash slowly. The game controller will continue to handle for about 30 seconds and then shut down automatically.

4) Game Controller turns ON/OFF/Charging/Sleep Model

a) TURN ON: Hold "N1" button for 5 second; TURN OFF: Hold "N1" button for 5 second until indicator lights turn off.

b) Low battery - Indicator light flash slowly; Fully Charged with USB port - 4 indicator light turn ON without flashing

c) Charging in shutdown status: Charging - 4 indicator light flash slowly; Fully Charged - 4 indicator light turn ON without flashing d) Pairing over 1 minute without connection: The game controller shut down automatically.

e) No action over 10 minutes paired: The game controller shut down automatically.

5) Reset the Game Controller:

a) When the game controller suspended/No response in , insert an elongated object into reset hole, press reset button once.

b) When the game controller cannot be paired, cancel pairing then turn it off and try again.

Highly recommend 2 Game Platforms to you! --> http://www.putaogame.com
Highly recommend 2 Game Platforms to you! --> http://www.putaogame.com
You can download and install those game simulators and games into your Android Device and play instantly!!

As Android is an open platform, each game was designed in different standard. Therefore, some of the game may not be run successfully. Please kindly understand the situation.