# **SMART WATCH**

# intelligent version







#### Rluetooth Watch Instructions

Thank you for choosing our **SMART WATCH** devices. You can read the manual, a comprehensive understanding of the use of equipment, in fact, with a taste of the function and simple method of operation.

This device is used as long as the brand of intelligent machines are adapted to use intelligent machines can synchronize phonebook and provides a variety of useful features and services to facilitate your work and leisure activities in the smart machine operation

The Company reserves the right to make any prior notice in the case of the contents of this manual for the right to amend, without notice

When you get **SMART WATCH**, and install the APK program on the smart phone, realize SMS, and other instant messaging reminders.

APK Access mode 1 : Download the smart phone two-dimensional code scanner



APK Access mode 2. Downloaded from Web address

IP Address: #ftp://211.144.196.251

User: Smart watch

Password: Smart watch

Smart phone after installing APK, and smart phone to SMART WATCH connection , First, open the Bluetooth feature on your smart phone, search SMART WATCH Equipment , smart phone will send "Bluetooth pairing request" and then press "confirm" ,After pairing SMART WATCH will prompt "\*\* (Connected) " while there will be a standby interface "o " icon indicates a successful connection has been your smart phone, connect after the success you can follow the instructions below SMART WATCH operations: Device explain:



- , Key Description: There are four buttons on the left upper and lower volume keys, page up and down keys, top right of the Enter key, the answer key bottom right of the switch button, back button, hold
- Standby screen displays: Time, day and date as the right



Main Menu Features:

the main menu: Standby screen, press the Enter key to enter the main menu interface. Main menu interface: In this interface adjustment.Page up and down keys to select a different function. and then press the ENTER button to enter.



1. Bluetooth Turn on Bluetooth after the following



two menus, such as the right



## (1) Bluetooth settings

- 1) Press the Enter key can be turned on or off Bluetooth. SMART WATCH Bluetooth turned off by default. Bluetooth is turned on if the status bar of the main menu screen will display a small icon "x".
- 2) The machine can be searched can be turned on or off. default is on
  - 3) The local device name display: SMART WATCH



### (2) Bluetooth sync

1) You can search for Bluetooth devices: 2) Display can be connected Bluetooth device name, press the Enter key can connect / disconnect, remove, and help functions.



2. Phone book If there is no sync phone book. press the Enter key displays "not connected", such as the right



Now press the Enter key for phone book access. prompt "Loading", such as



, Loaded successfully, you can view the phone book down keys. Successful synchronization phone book. press the Enter key to enter the contact list screen: Tap the contact

| can be a phone call functionality.   |       |     |      |
|--|-------|-----|------|
| 3. Remote Notification in the latter of the latter synchronization information, this feature only shows the  | obile | e p | hon  |
| 4. Bluetooth music : If a Bluetooth with   | th co | nne | ctio |
| 5. another phone, press the Enter key to enter the   | H     | II  | ы    |
| interface. In this interface, the OK button to play or volume key up or down when the music player can swi adjust the volume, you can press the Back key to retuscreen | tch s | ong | s: T |

. Then press the volume key up or down to adjust the other smart phones connected thereto adjusting the volume also can increase or decrease the volume of SMART WATCH play music and vice versa if not even prompt box will pop up on the "not connected."

未连接

NOTE: To ensure consistency with other phones Media Audio connection in order to play music!

Messaging 5. Information : If the remote device supports the MAP protocol (such as Samsung GLAXY 2, millet, 2, etc.), press the Enter key to enter, you can see the In box and Sent two menu two menu message list; if the remote phone does not support MAP protocol (go to the In box and Sent messages prompt "remote device does not support MAP"), the remote device is installed "Bluetooth notice" APK, remote notification view the latest messages.

6. Call records : Press the Enter key to see:

missed calls, dialed calls, received calls, and all calls, such as the



7.Pedometer:Calculation of the walking distance of time (time, minutes, seconds) and the number of kilometers (km). Open this function will see the following menu-

1) Pedometer ~ In the menu and press the left software trigger start step-by-step, the total distance (km), Kaluri (kcal) calculation.

2) Last Record ~ The minutes of the last step, the total distance, calories walking time

3) Step Setting(CM) ~ According to height ratio setting step distance

4) Weight setting(KG) ~ According to its own weight set 8. Remote capture: Remote on/off mobile phone camera press

confirm to complete pictures 9.Anti lost: Watch wil send alarm after leaving the mobile phone a

certain distance. Open this function will see the following menu. 1) Enable

2) Set distance~can be long distance mid-distance close distance.

Organizer 10. Toolbox :Open the Toolbox has the following



menus, such as the righ

(1) Language Settings: Enter this interface Support Chinese and English native default is Chinese press the Enter key to select to select the appropriate language. Press the Return key to exit this function:

(2) Time setting: There are two ways to set the time.

 Press the Enter key to enter this interface button to jump to different locations numeric setting, each location can press the volume keys up or down to adjust the specific numbers. setting completed, press the Enter key to save the settings.

 Installed on the smart machine "Bluetooth notification" APK, when connected to the phone dialer, the dialer client will prompt "with the remote device's date and time synchronization?". Then press the Enter key can be time synchronized to the phone dialer side, so there is no need to manually adjust the time.

(3) Date Set: There are two ways to set the date

2013/09/23

 Press the Enter key to enter this interface the switch button to jump to different locations numeric setting, each location can press the volume keys up or down to adjust the specific numbers, setting completed, press the Enter button to save the

2) Installed on the smart machine "Bluetooth notification" APK, when connected to the phone dialer, the dialer client will prompt "with the remote device's date and time synchronization?". Then press the Enter key can be synchronized to the phone dialer end date . so no need to manually adjust the date

(4) Rinatone: enter ringtones function, vibration and ringtone 1-4 to select, simply choose the ringtone press the Enter key after the prompt above the "Saved" is set successfully.

00:00

□ 00:00

(5) Stopwatch : Press OK to start timing or pause. press the return key to exit this function

(6) Alarm: Press the Enter key to enter the alarm interface

Alarm clock can be set to 5, press the volume up and down keys to select an option, press the Enter key to enter this



1) Alarm status: Press the Enter key to enter the selection and preservation of the interface, the default is off, press the Enter key

you can choose to open or close, as the right is complete press the Enter key to save the settings, such as the right



2) Set the time 10:00 : Press the switch button to jump to different locations numeric setting, each location can press the volume keys up or down to adjust the specific numbers, setup is complete press OK to save the settings

3) Ring type: Press the Enter key to enter the selection and save screen, press the up and down volume keys can be set once or daily (the default one) or a customized setup is complete press the OK button to save the settings.

4) Alarm tone: Press the Enter key to enter the alarm tone screen. press the up and down volume keys can be set to select the alarm tone, setup is complete press the Enter key to save the settings Note: Set the alarm is complete, set the alarm if opened, the list box will interface to select the tick.

. The status bar will be the standby interface Alarm "@," small icons; alarm sound, press the Enter key to stop the

(7) Power saving mode: use "confirmation" open or close (8) About Bluetooth Watch: Enter this function to display SMART

WATCH version information