Thank you for purchasing the Bluetooth Digital Transmitter. This user manual is designed to familiarize you with all the features of this device. It will help you operate the Bluetooth Digital Transmitter. Please take time to read this user manual carefully, even if you are already familiar with a similar product.


### Bluetooth Music Transmission Technology

Bluetooth is a short distance communication (generally within 10m) radio technology. In the exchange of information between mobile phone, include wireless headset, notebook computer, IT digital equipment. Use "Bluetooth" technology, allowing communication between simplified equipmenteffectively. Thus the data transmission become more quickly and efficiently.

### Introduction

This product is a Bluetooth Digital Transmitter. It allows you to get rid of the bondade of all kinds of cables, Whether you are in a comfortable sofa or move in the room, it can deliver music from your TV/B<sub>IU-TAY</sub> DVD to your Bluetooth speaker / Bluetooth headphone/ home stereo system, make u enjoy the abundance of private music feast.

#### Part Names and Functions



- 1. Status Indicator
- 2. Optical input
- Coaxical input
  Power switch
- 4. Power switch
- 5. 3.5mm audio input
- Charging

| Specification           |           |
|-------------------------|-----------|
| Bluetooth specification | A2DP/IOPT |
| Memory group number     | Ten       |

| Bluetooth Frequency                           | 2402~2480MHz |
|---|--------------|
| Power supply                                  | 5V/500MA     |
| Effective Distance                            | 10m .        |
| Dimension                                     | 91*57*27mm   |
| Audio R/L output specifications               |              |
| input level                                   | 2+/-10% Vrms |
| Frequency response                            | 20Hz~20KHz   |
| The L/R channel isolation                     | -45dB /      |
| SNR (signalto noise ratio, nominal Audio R/L) | ≥90kB        |
| THD (nominal, Audio R/L)                      | 0.05%        |
| Optical input specifications                  |              |
| Wavelength (nominal)                          | 640~670nm    |
| Optical power input (nominal)                 | -17Bm        |

# Product features

 Support A2D/IOPT using the latest Bluetooth 2.1 technology, support A2DP agreement, not only greatly improve the data transfer rate, more to ensure the stability of audio and sound quality.

This product can be used with what equipment:


- If your device with Bluetooth function, and support Bluetooth A2DP agreement, can be used with this product. Such as: TV, BLU-ray DVD, iPhone, other brand mobile phones and ordinary computers, etc.
- This product can memory 10 groups device which paired with it already, and automatically paired when next time you use.
- 4.This product uses optical fiber, coaxial line and 3.5mm audio input, ensurethe super sound quality and easy to connect with all devices.
- 5. Transmission distance up to 10m.

### How to use?

- Before you using, please make sure your bluetooth device supports A2DP.
- Use optical fiber line or coaxial line or stereo audio line connect with the sound system, or TV/BUL-ray DVD, or computer.
- 2. Connect Bluetooth Digital Transmitter with power supply. (light flashing quickly)
- Open the Bluetooth music equipment, eg, Bluetooth speaker/ Bluetooth headphone etc. and pairing (pin code:0000), after the success of the pairing, light will blink slowly.
- Play music with sound source equipment, enjoy your music feast. Indicator light flickers as the music played.

2

#### Connection



## Accessories

Bliuetooth Digital Transmitter Optical cable USB charge cable power adapter user manual

#### Note

- Do not place this prodiuict in the liquid environment or exposed to moisture or high temperature environmennt.
- 2. Don't use corrosive liquid to cleann this product.
- 3. Don't touch with sharp objects,or the surface maybe scratched.
- 4. Don't open the product, it may cause internal components damaged.
- If no need use this producct for a long time, please put the device in dry environment to avoid high or very low temperature, away from damp and dust

# Warranty time:One year