
Many thanks for purchasing our product! This is a portable wireless control, used for mobile phone,MID,TV box, smart TV,PC and so on.It can be used as gamepad, wireless mouse, music control, e-book page, PPT presentation etc.and support iOS, Android Windowspragate system and so on.

Important Note: Products are subject to change without any notice. And this product has applied for patents, counterfeiting is not pemitted.

Oproduct sketch map:









1.Power on/off and pair connection(power mode introduction)

① Power On: Press START button until LED is on (about 2 seconds).Default is automatic mode.

Power on mode changing instruction(please operater on power off mode)

Stand automatic mode: Press A button, then press START to power on. Mouse light

will be on first, this is standard mode;
Android MTK mode: Press Y button, then press START button to power on, charging



Power on

Press **START** button until LED is on (about 2 seconds). Default is automatic mode.

Apple iCade mode: Press B button, then press START button to power on, GAME light will be on first, this is Apple iCade mode;

Apple iOS mode: Press X button , then press START button to power on, KEY light will be on first, this is Apple iOS mode;

Remark:(1)when use the specified mode for first time, then press START button to power on next time, remote will default specified mode before. If need shift to other mode, please refer to above power on mode.

(2) Under stand automatic mode, when connected with Android equipment then it is stand Android mode, when connected with Apple equipment, then change to Apple iCade mode, if under other mode device can't shift mode automatical.

Power off

Long press START button, LED light will flash to off(about 5 seconds), device will power off.

Note: If no connecting with Bluetooth device after 5mins, system will power off

② Power off: Long press START button, LED light will flash to off (about 5 seconds), device will power off. Note: If no connecting with Bluetooth device after Smins, system will power off authorisation, after connecting with Bluetooth device, if no any operation, system will power off after Smins.



Pair and connect

after power on, LED will flash, the device will enter into the Bluetooth pair mode automatically to find the address and name of this device(X-039-XXX), click then can connect

- ③ Pair and connect: after power on, LED will flash, the device will enter into the Bluetooth pair mode automatically to find the address and name of this device(X-039-XXX), click then can connect. Pair and connect successfully, LED indicator will turn off. Next power on, it can connect and match the last Bluetooth device. Under turn off statelong press START button more than 8 seconds, LED will flash, then go to pair mode again, and can't connect last paired device automatically.
- 2.GAME function:(Turn side switch to Game side, now device is operated by two-hands horizontal.)

Standard Android device: In Menu, if joystick can move cursor, X, Y button is confirmation button, A B button is returning key; this means your mobile system can

support international standard gamepad, just download game and play directly (If can't operate, then refer to part ②, Android MTK mobile operation)

Game Download: use QR code software to scan QR code on the device (or enter into website:http:// www.mocute.com) to enter into ZHUZILIN download center, then you can download ZHUZILIN game application or third party's

game application. ZHUZILIN Game center have all gamepad games, and support NES/GB/GBC/SFC/SMD/GBA/N64/MAME/PS games. Users can also download simulator BIN files to Games file folder in mobile, then can use ZHUZILIN software to open the game file, like many famous games: Super Mario, Metal Stug, Sangokushi and so on:

Android games usually have gamepad type, download this kind of games, just connect with Bluetooth then can operate with gamepad directly, this kind of games are like: Eternity Warriors 2, FIFA 15 and so on. (Some games maybe need set to use gamepad control when playing)

Senior game combination key :

L1=SELECT+A R1=SELECT+B right loystick=left loystick+START L2=SELECT+X R2=SELECT+Y

② Android MTK mobile operation.tike Redmi 3G version, Huawei Honor3X, CoolPAD, Zhongxing, these old style mobiles use MTK CPU, due to MTK bed compatibility, they can't support international standard gamepad agreement. So if by standard Android connection method, unusual problems will happen. We preset MTK mode to support 2HUZILIN games.

Before play games, please set keyboard input mode to English input and can input English letters then ok. Next., please connect with Bluetooth and enter games then can play (Some games maybe need set to use (Cade when playing)

Combination key: L1=SELECT+A R1=SELECT+B

when connected with control, if soft keyboard can't work, please hit M button or

- 3.KEY mode function(please turn switch to KEY on device side, now device is operated by single hand and multimedia function buttons work on back)
- (1) Android devices: X button is Volume+, A button is Volume-, B button is mute. Y button is returning key:

Music function operation: after connected with bluetooth, open media player(like SAMSUNG's media player), and play music, now our remote can do some operations: like stop, play pause changing songs and so on. Long pressing

previous/next can forward/backward.

Self-shutter: Android/Apple mobile use "camera" to take photoes, Android mobile like SAMSUNG can use Volumn to adjust focus length, other Android mobile can go into camera setting to set volume for taking photo or scan barcode to download ZHIIZHIII Na analication software then can use camera directly.

E-Book page up and down:leader use Volume+/- to page, Kindle use jokstick to page.

Mouse function-Pressing M button, then yellow MOUSE indicated light ill be long on, now mouse and work joystick can move, SELECT is for left key of mouse, START is right key of mouse, top button is mouse long-pressing function, when pressing top button, MOUSE indicated light will flash, now moving mouse can achieve drag function or pressing top button and using joystick to achieve drag function.

②Apple device: X button is Volume+, A button is Volumne- B button is mute, Y button is HOME, Musice and self-shutter is same with Android device. Apple device don't support mouse function.

Key-locked function

After device connocted, pressing SELECT and M button at the same time, can lock all keys beside START key(Means other keys can't work), and pressing SELECT and M button at the same time again can unlock, when buttons locks, KEY and GAME indicated light will flash at the same time.

5.Charge

Our product is with inner rechargeable lithium battery, when power is low, charging red LED will flash.Please insert 5V USB port to charge, then charging LED will be on. And when power is full,charging LED will be off.

Notes: 1. When accident cause not boot or unable to shutdown, please use needle to press Reset button on side.

2.If already paired ,but can't connect, please cancel the pair and boot the device and connect again.

Item	SPEC
SIZE	92mm*40mm*10mm
weight	27 gram
wireless protocol	wireless 3.0 compliant
wireless distance	2-10 meters
os	Android /iOS/PC
Battery	Rechargeable lithium battery 100mA
Working time	About 10hours
Recharging current	5V <200mA





START.....




ON/OFF

Press START button until LED is on (about 2 seconds) . Default is automatic mode.



Pair and Connect


After power on, LED will flash, the device will enter into the Bluetooth pair mode automatically to find the address and name of this device(X-039-XXX), click then can connect



Mode Change

Press **M** button, change mouse mode.

Toggle Switches to change **GAME** or **KEY**mode.



Multimedia function Button

Multimedia keys for operations such as pause and down song.



Download

Support massive resources