

TVPRO

Setup & User Guide

TVPRO.SUPPORT

CONTENTS

Section 1: Introduction.

- 3. What's in the box
- 4. TVPRO overview
- 5. Hardware features

Section 2: Set up.

- 6. TVPRO Navigation
- 7. Connecting to Network
- 8. Language & Settings
- 9. Technical Specs

Section 3: Air Mouse Remote.

- 10. TVPRO air mouse features
- 11. Using your remote
- 12. Remote functions

INTRODUCTION


TVPRO is the first patent pending interactive media player with a Full 1080p HD webcam. It transforms any TV into a "Beyond Smart" TV that can now provide the same experience you enjoy from your computer and mobile devices every day. Any TV can now become an intelligent, interactive portal to entertain and communicate with the world. TVPRO is powered by Android giving you access to over a million apps, movies, TV shows, music, games and more through the Play store.

What's in the box



Note: Your power supply may look different from the one pictured here.

TVPRO OVERVIEW





Power Button

Start TVPRO by short press; shut down the TVPRO by long press.



Dual Microphones

Dual noise cancelling microphones support hands free video conference up to 15ft+.



Dual Speakers

TVPRO has dual speakers to provide an independent audio solution when using with a display or monitor that has no audio.



1080p HD Webcam

TVPRO has a full 1080p HD webcam that brings a high quality live video conferencing solution to any TV.



(2) USB ports

The dual USB ports support the air mouse remote, external hard drive, mouse & keyboard, 3G dongle and gaming pads.



HDMI port

Connect TVPRO to the HDMI port of a high-definition TV using the provided HDMI cable.



Built-in 802.11bgn Dual Band Wi-Fi technology

Connect TVPRO to your 2.4G or 5G supported wireless network.



LAN Ethernet port

If your network is Ethernet-based, connect an Ethernet cable.



Bluetooth

Bluetooth 4.0

Enable Bluetooth to connect to any Bluetooth compatible device such as headphones, microphone, speaker, keyboard and other wearable devices.

TVPRO SET UP



Home screen:

When you first turn on your TVPRO, you'll see the home screen with the favorites tray that is a quick way to access your most used apps.



Key Navigation Buttons:

Back



Opens the previous screen you were working in, even if it was in a different app. Once you back up to the Home screen, you can't go back any further.



Home

Opens the central Home screen. To open Google Now, swipe up.



Recent apps

Opens a list of thumbnail images of apps you've worked with recently. To open an app, touch it. To remove a thumbnail from the list, swipe it left or right.



Voice Search
"Ok Google"



All Apps
Icon



Settings
Menu



Additional
Info

CONNECT TO NETWORK



Wi-Fi Setting:

Click the "Wi-Fi" toggle ON and choose your network connection to input password.



Ethernet Setting:

Click the "Ethernet" tab and check the "Use Ethernet" option. Make sure the Wi-Fi setting is turned off.



LANGUAGE & SETTINGS



Change Language:

Click the "Language & Input" tab and choose the language of preference.



Set App security:

Click the "Security" tab and check "Unknown Sources" to allow all applications to run on TVPRO.



TECHNICAL SPECS



Operating System
Android 4.4 KitKat



Processor
A31s ARM Cortex - A7 Quad-Core



Memory
DDRIII 2GB



Storage
Nand Flash 8GB



Camera
Full 1080p HD



SD Storage
Micro SD card: 1GB/2GB/4GB/8GB/16GB/32GB



Connectivity
WiFi 802.11 BGN, Ethernet (100M), Bluetooth 4.0, HDMI, (2) USB 2.0



Video
RM/RMVB, MPEG, MKV, AVI, MP4, MOV, FLV, H.263, H.264, VC1, DivX, Xvid, TS, RealVideo, VP6, VP8 up to 1080p



Audio
AAC-lc, heaac/he-aac, v2, ac3, amr-nb, dts, mp3, ogg, wma, lpcm/pcm/adpcm, fla



Features
Miracast, DLNA, XBMC, WiFi Hotspot, Office Suite, Local Media playback HDD, uDisk, SD card, Flash 11.0+

AIR MOUSE REMOTE FEATURES

Key Features:

- 2.4Ghz wireless technology
- Works with android, windows, mac os, linux
- REchargeable lithium-ION battery
- 3-axis gravity + 3 axis gyroscope sensors
- Range from 25 - 40 feet
- IR learning key functions
- Anti-shake allows precision mouse operation
- Motion gaming support



Air Mouse
Point & Click




Motion
Gaming





QWERTY
Keyboard



IR Learning
Features



AIR MOUSE FUNCTIONS



Change mouse pointer speed (4 levels):

Pressing and at the same time for 3 sec with speed up or slow down the air mouse movement level. The red and blue LED will flash 1-4 times to indicate the mouse speed setting.

IR remote control learning function:

Pressing and at the same time for 3 sec will activate the IR learning mode and indicator LED will start flashing. Next, press and release the IR Key that you want to code and the LED will flash slower. Place the air mouse remote IR emitter directly pointing 1cm away from the other remote IR and press the button on that remote that you want to be learned. The IR LED will go from flashing to constant indicating the code has been successfully learned.

AIR MOUSE FUNCTIONS

Code Pairing the Remote and Nano Key:

If the remote does not connect automatically, you will need to pair with the nano key by pressing and buttons at the same time and hold for 3 seconds. The remote LED will flash rapidly, re-insert the USB nano key and hold the remote close to the receiver in 30cm, when code pairing succeeds, the LED will slowly flash 3 times.

Use the Air Mouse Function:

Click or on the respective side of the remote to start the air mouse which allows the cursor to move in any direction the remote is pointed. Pressing any key when the "Qwerty" keyboard side is up will rotate the mouse orientation 90 degrees to compensate and pressing any of the directional arrow keys will stop the air mouse function.

Power Saving Mode:

The air mouse function will stop if no movement of the remote for 30 seconds or if no buttons are clicked for 10 minutes the remote will enter power saving mode.

Zero Drift Correction and Calibration:

If the mouse cursor drifts without movement of the remote, just make the remote stay still 3-4 seconds on a desk to eliminate the drift. Calibrate cursor accuracy by moving it to an edge of the TV until it stops and then point the remote directly at the cursor to align.

Recharging Battery:

When the remote battery is low the power LED will rapidly flash red. Recharge the lithium-ion battery by connecting the remote with the micro USB cable to a computer or 5v DC power supply. During recharging the power status LED will flash green and red until the battery is full and the light will remain green. The total recharging time is about 60 to 90 minutes.

ONE (1) YEAR HARDWARE LIMITED WARRANTY

Warranty Policy: This Limited Warranty is made to the original purchaser only.

Limited Warranty: This Limited Warranty is limited to defects in materials and workmanship of the product as supplied by the manufacturer.

Warranty Period: The Limited Warranty period begins on the date of purchase, as stated on the sales receipt, and extends 365 days from that date.

What is covered: This Limited Warranty covers defects in materials and workmanship under normal installation, use and service. If defect arises during the Warranty Period, Limitless Innovation Inc. will, at its option, replace your part, repair your part, or refund your money for any part that it sells that fails during the warranty period. Replacement parts provided as warranty replacement carry the remainder of the original warranty term or 365 days from the date of exchange, whichever is longer, subject to the conditions and exclusions in this warranty.

What is not covered: This Limited Warranty does not cover damage resulting from abuse, accident, modifications or other causes that are not defects in materials and workmanship. Other than the consumer law rights to which you are entitled, all warranties, conditions and other terms not set out in this warranty document are excluded from this One-Year Limited Warranty. Some countries do not allow limitations on how long such warranties, conditions and/or implied terms may last, so the limitation described above may not apply to you.

Limitless Innovation does not warrant, represent or undertake that it will be able to repair or replace any Product under this warranty without risk to and / or loss of information and / or data stored on the Product. In no event shall Limitless Innovation be liable for any losses of information or data from a warranty return.

PRODUCT RETURN POLICY

Before returning any product you believe is defective, you must contact Limitless Innovation by telephone or email and provide details of the warranty claim situation and the product serial number printed on the bottom of the product. A Return Authorization Number ("RAN") for the product must be issued by Limitless Innovation Inc. prior to the return of any product for a warranty claim. You must then return the defective product to Limitless Innovation Inc., shipping costs prepaid, and include the RAN clearly on the outside box. Your original receipt or other proof of purchase and a legible description of the problem must be included with the returned product. Any Claim for shortage or shipping damage must be accompanied by the Store Receipt or Packing Slip and the registration number from the web or paper registration, and must be submitted within 30 days of receipt or invoice date, whichever is later. Damages in shipment are the responsibility of the carrier and you must make a claim directly with the carrier. Returns to be sent to the below address if advised by Limitless Innovation in writing.

Register your TVPRO @ www.tvpro.us/register

TVPRO Inc. - Limitless Innovation Inc.

© 2014 TVPRO Inc. All rights reserved.

Under the copyright laws, the TVPRO set up and user guide manual may not be copied, in whole or in part, without the written consent of Limitless Innovation Inc. Every effort has been made to ensure that the information in this manual is accurate, however Limitless Innovation Inc. is not responsible for printing or clerical errors.

Patent Notices:

The TVPRO device and methods used in association with the TVPRO device and Limitless Innovation Inc. platform technologies may be covered by one or more patent pending applications in the U.S. and other countries.

Trademark Notices:

TVPRO, BEYOND SMART and RESHAPE are trademarks of Limitless Innovation Inc. and or its affiliates and are not to be reproduced without expressed written permission. All other brands, product names, company name, trademarks, and service marks are the properties of their respective owners.

Additional Information:

TVPRO Terms of Use, User Manual, Customer Support and other TVPRO information can be found at tvpro.support.

Limitation of Liability:

ANY LIABILITY FOR CONSEQUENTIAL, INCIDENTAL, SPECIAL, EXEMPLARY OR PUNITIVE DAMAGES IS EXPRESSLY DISCLAIMED. THE LIABILITY OF LIMITLESS INNOVATION INC., AND OF ITS EMPLOYEES, AGENTS AND ASSIGNS, IN ALL EVENTS SHALL NOT EXCEED THE PURCHASE PRICE PAID FOR THE PRODUCT. REPAIR, REPLACEMENT, OR PAYMENT OF SUCH AMOUNT BY LIMITLESS INNOVATION INC. SHALL BE THE FINAL AND EXCLUSIVE REMEDY AND SHALL NOT BE CONSTRUED OR ALLEGED BY CUSTOMER TO HAVE FAILED OF ITS ESSENTIAL PURPOSE. ALL LIABILITY OF THE COMPANY SHALL CEASE WITH THE EXPIRATION OF THE 365-DAY WARRANTY PERIOD.

Need more **information?**

Visit **TVPRO.SUPPORT** to get the most out of your
TVPRO interactive experience.



TVPRO.SUPPORT

Check out our instructional videos, FAQ's or contact a
TVPRO support specialist.