

BLUETOOTH WATCH INSTRUCTION

Thank you for using our bluetooth watch , in order to learn how to use it, please read this instruction carefully before using.



B

MAIN FUNCTION

MAIN FUNCTION





- A: Caller's name and number display (name and number)
- B: Unconnection warning after.5-10M(vibration warning)
- C: incoming vibration for alert
- D: answer/conversation/dialing/hangup
- E: synchronization/check/wipe Data
- F: time display

C






FUNCTION

FUNCTION

1. dial key/confirm key

- A: In standby mode, please press number key first, then press  to call
- B: In synchronization/check/wipe Data/time adjust mode, please press  to  confirm.
- C: in incoming mode, please press  to answer.

2. hangup key

- A: in poweroff mode, long press  for 3 seconds to switch to power-on
- B: in poweroff mode, long press  for 5 seconds to show Bluetooth matching.
- C: in incoming mode, press  to reject calls
- D: in conversation mode, press  to hangup
- E: in standby mode, long press  for 3 seconds to switch to power-off.

3. V+

- A: in standby mode, long press V+ for 3 seconds to switch to time adjustment mode, and one more second to adjust time.
- B: in conversation, press V+ to increase volume




4 V-

- A: in standby mode, long press V- for 3 seconds to switch to Synchronization/Check/Wipe Data mode.
- B: in conversation, press V- to increase volume




SETTING



1. bluetooth matching

In poweroff mode, long press  for 5 seconds to show Bluetooth matching condition. Then open Bluetooth of cellphone to search targets. A sign of  indicates that cellphone has found watch Bluetooth device. Select  on the cellphone, choose password 0000; If a cellphone is matched, there will be words and vibration reminding success. There is a earphone-like mark on the left side of the watch indicating success connection.

2.Synchronization

In standby mode, long press V- for 3 seconds to switch to Synchronization/Check/Wipe Data mode. Then, press  to synchronize, after 1 minute,


3 .Number Check

After synchronization, In standby mode, long press V- for 3 seconds to switch to Synchronization/Check/Wipe Data mode; press V+ to switch to Check, then press  to enter into phone book. Press V+ V- to check, select phone number, then press  to dial.



4 .Phone book Empty

After synchronization, In standby mode, long press V- for 3 seconds to switch to Synchronization/Check/Wipe Data mode. Press V+ to switch to Wipe Data, there press  to clear phone book.

5. Time Adjustment


In standby mode, long press V+ for 3 seconds to switch to time adjustment mode, at this time, time bounces, then press V+ V- to adjust time,  confirm.

DIAL

- A: in standby mode, open the cover of the watch, press the numbers, then press  to dial.
 B: switch to check number, choose the number, then press  to dial.

DISASSEMBLE AND ASSEMBLE WATCH

- A: press disassemble & assemble button and turn the cover upward, then disassemble the body parts
 B: press disassemble & assemble button and turn the cover upward, then assemble the body parts.



TECHNICAL SPECIFICATION

- A:compatible to Bluetooth 2.1 (standard)
 B:Class 2 standard (10 meters)
 C:conform to Bluetooth hands-free standard (Hands-free Profile) V0.96
 D:working temperature -20°C ~ +75°C storage temperature -40°C ~ +85°C
 E:workable distance 5-10M
 F:auto energy-saving mode
 G:low power consumption mode/ high speed operation mode
 H:safety certificate, data encryption